

Water Flow Information for Pumping and Hydroelectric Design

Flow Through Nozzles

The chart below shows flow through various nozzles in GPM at a range of heads from 5 feet to 400 feet. Use chart to choose what nozzle size to use and how many nozzles a turbine must have to give the required flow to use all of the water available in the system

Head		Nozzle Diameter											RPM for 4" Turbine
Feet	PSI	1/8"	3/16"	1/4"	5/16"	3/8"	7/16"	1/2"	5/8"	3/4"	7/8"	1.0"	
5	2.2	-	-	-	-	6.18	8.4	11	17.1	24.7	33.6	43.9	460
10	4.3	-	-	3.88	6.05	8.75	11.6	15.6	24.2	35	47.6	62.1	650
15	6.5	-	2.68	4.76	7.4	10.7	14.6	19	29.7	42.8	58.2	76	800
20	8.7	1.37	3.09	5.49	8.56	12.4	16.8	22	34.3	49.4	67.3	87.8	925
30	13	1.68	3.78	6.72	10.5	15.1	20.6	26.9	42	60.5	82.4	107	1140
40	17.3	1.94	4.37	7.76	12.1	17.5	23.8	31.1	48.5	69.9	95.1	124	1310
50	21.7	2.17	4.88	8.68	13.6	19.5	26.6	34.7	54.3	78.1	106	139	1470
60	26	2.38	5.35	9.51	14.8	21.4	29.1	38	59.4	85.6	117	152	1600
80	34.6	2.75	6.18	11	17.1	24.7	33.6	43.9	68.6	98.8	135	176	1850
100	43.3	3.07	6.91	12.3	19.2	27.6	36.6	49.1	76.7	111	150	196	2070
120	52	3.36	7.56	13.4	21	30.3	41.2	53.8	84.1	121	165	215	2270
150	65	3.76	8.95	15	23.5	33.8	46	60.1	93.9	135	184	241	2540
200	86.6	4.34	9.77	17.4	27.1	39.1	53.2	69.4	109	156	213	278	2930
250	108	4.86	10.9	19.9	30.3	43.6	59.4	77.6	121	175	238	311	3270
300	130	5.32	12	21.3	33.2	47.8	65.1	85.1	133	191	261	340	3590
400	173	6.14	13.8	24.5	38.3	55.2	75.2	98.2	154	221	301	393	4140

Pipe Loss Chart

Use the chart below to determine what pipe size is required to efficiently allow necessary flow for your power need. Once you know the required flow for your system (gpm), find the head loss for various pipe sizes. Multiply the head loss number by the length of the pipe divided by 100 and you will get the loss of head for that pipe size. The actual head minus the head loss will give you the effective head in the system.

Pipe Diameter (inches)	Flow (GPM)																							
	1	2	3	4	5	7	10	15	20	25	30	40	50	60	70	80	100	150	200	250	300	400	500	
1/2	2.08	4.16	8.7	14.8	23.5	43																		
3/4	0.51	1.02	2.2	3.7	5.73	10.5	20.1	42.5																
1	0.1	0.55	0.68	1.15	1.72	3.17	6.02	12.8	21.8	32.9	46.1													
1-1/4	0.03	0.14	0.19	0.31	0.44	0.81	1.55	3.28	5.59	8.45	11.9	20.2	30.5	45.6										
1-1/2		0.07	0.08	0.13	0.22	0.38	0.72	1.53	2.61	3.95	5.53	9.43	14.3	20	28.6	36.7								
2			0.03	0.05	0.07	0.11	0.21	0.45	0.76	1.15	1.62	2.75	4.16	5.84	7.76	9.94	15.1	34.8	59.3					
2-1/2				0.03	0.04	0.05	0.09	0.19	0.32	0.49	0.68	1.16	1.75	2.46	3.27	4.19	6.33	13.4	25.0	37.8	46.1			
3					0.02	0.03	0.07	0.11	0.17	0.23	0.4	0.6	0.85	1.13	1.44	2.18	4.63	7.88	11.9	18.4	40.1			
4								0.03	0.04	0.06	0.11	0.16	0.22	0.3	0.38	0.58	1.22	2.08	3.15	4.41	7.52			
5										0.03	0.04	0.05	0.07	0.1	0.13	0.19	0.4	0.69	1.05	1.46	2.49	3.76		
6												0.02	0.03	0.04	0.05	0.08	0.16	0.28	0.43	0.6	1.01	1.53		

12 VOLT 2% WIRE LOSS CHART

Maximum distance one-way in feet of various gauge two conductor copper wire from power source to load for 2% voltage drop in a 12 volt system. Do not exceed the 2% drop for wire between PV modules and batteries. A 4 to 5% loss is acceptable between batteries and lighting circuits in most cases. Multiply distances by 2 for 24 volts and by 4 for 48 volts.

AMPS	#14	#12	#10	#8	#6	#4	#2	1/0	2/0	4/0
1	45	70	115	180	290	456	720			
2	22.5	35	57.5	90	145	228	360	580	720	1060
4	10	17.5	27.5	45	72.5	114	180	290	360	580
6	7.5	12	17.5	30	47.5	75	120	193	243	380
8	5.5	8.5	15	22.5	35.5	57	90	145	180	290
10	4.5	7	12	18	28.5	45.5	72.5	115	145	230
15	3	4.5	7	12	19	30	48	76.5	96	150
20	2	3.5	5.5	9	14.5	22.5	36	57.5	72.5	116
25	1.8	2.8	4.5	7	11.5	18	29	46	58	92
30	1.5	2.4	3.5	6	9.5	15	24	38.5	48.5	77
40			2.8	4.5	7	11.5	18	29	36	56
50			2.3	3.6	5.5	9	14.5	23	29	46
100					2.9	4.6	7.2	11.5	14.5	23
150							4.8	7.7	9.7	15
200							3.6	5.8	7.3	11

Maximum Ampacities for Copper & Aluminum Wire

Allowable ampacities of conductors (wires) in conduit, raceway, cable or directly buried, based on ambient temperature of 30°C (86°F). NEC allows rounding up cable ampacity to next size standard fuse or breaker.

Wire Size (AWG)	Copper Conductor Temp. Rating		Aluminum Cond. Temp. Rating	
	75°C (167°F)	90°C (194°F)	75°C (167°F)	90°C (194°F)
*14	20	25		
*12	25	30	20	25
*10	35	40	30	35
8	50	55	40	45
6	65	75	50	60
4	85	95	65	75
2	115	130	90	100
1	130	150	100	115
1/0	150	170	120	135
2/0	175	195	135	150
3/0	200	225	155	175
4/0	230	260	180	205

Temperature Correction Factors

For ambient temps. above 30°C (86°F), multiply the allowable ampacities shown at left by the appropriate factor shown below:

Temperature Range	75°F insul.	90°F insul.	
31-35C	87-95F	0.94	0.96
36-40C	96-104F	0.88	0.91
41-45C	105-113F	0.82	0.87
46-50C	114-122F	0.75	0.82
51-55C	123-131F	0.67	0.76
56-60C	132-140F	0.58	0.71

* The national electrical code (NEC) specifies that the overcurrent protection device not exceed 30A for 10 AWG wire, 20A for 12 AWG wire and 15A for 14 AWG wire.